

STEAM WIZARD 1000/2000

DMX CONTROL TABLE



Channel	Value			Function
1	000			No function
	001	-	255	Fog output low -> high
2 (lighting duration $\hat{=}$ fog output duration)	000	-	004	Blackout
	005	-	255	Dimmer low -> high
3	000	-	005	No Strobe
	006	-	255	Strobe <1Hz -> 30Hz
4 (colour preselection ~ 5 sec. lighting duration)	000	-	005	Colour off
	006	-	013	Colour 1 Red
	014	-	021	Colour 2 Green
	022	-	029	Colour 3 Blue
	030	-	037	Colour 4 Amber
	038	-	045	Colour 5 Red-Green
	046	-	053	Colour 6 Red-Blue
	054	-	061	Colour 7 Red-Amber
	062	-	069	Colour 8 Green-Blue
	070	-	077	Colour 9 Green-Amber
	078	-	085	Colour 10 Blue-Amber
	086	-	093	Colour 11 Red-Green-Blue
	094	-	101	Colour 12 Red-Green-Amber
	102	-	109	Colour 13 Red-Blue-Amber
	110	-	117	Colour 14 Green-Blue-Amber
	118	-	125	Colour 15 Red-Green-Blue-Amber
	126	-	127	Colour Jumping Stop
128	-	191	Colour Jumping Speed slow -> fast / Colour 1 -> 14	
192	-	255	Colour Fading Speed slow -> fast / Colour 1 -> 14	

