

CL 200

DMX CONTROL TABLE



1CH Mode					
Ch.	Function	Values			
1	Dimmer	000	-	255	0% to 100%

2CH Mode 1					
Ch.	Function	Values			
1	Dimmer	000	-	255	0% to 100%
2	Colour Temperature	000	-	005	CT off / Full on depending on Dimmer
		006	-	255	7800K - 3200K

2CH Mode 2					
Ch.	Function	Values			
1	Warm White	000	-	255	0% to 100%
2	Cold White	000	-	255	0% to 100%

3CH Mode					
Ch.	Function	Values			
1	Dimmer	000	-	255	0% to 100%
2	Strobe	000	-	005	Strobe open
		006	-	255	Strobe slow -> fast <1Hz - 30Hz
3	Colour Temperature	000	-	005	CT off / Full on depending on Dimmer
		006	-	255	7800K - 3200K

4CH Mode					
Ch.	Function	Values			
1	Dimmer	000	-	255	0% to 100%
2	Strobe	000	-	005	Strobe open
		006	-	255	Strobe slow -> fast <1Hz - 30Hz
3	Warm White	000	-	255	0% to 100%
4	Cold White	000	-	255	0% to 100%