

PAR 64 LED CAN

DMX CONTROL TABLE



2-CHANNEL MODE		
CHANNEL	VALUE	FUNCTION
CH1	000 - 255	Master dimmer (0 - 100%)
CH2	000 - 255	Colour Macros:
	000 - 016	Red
	017 - 033	Green
	034 - 050	Blue
	051 - 067	White
	068 - 084	Amber
	085 - 101	UV
	102 - 118	Yellow
	119 - 135	Cyan
	136 - 152	Lavender
	153 - 169	Light Green
	170 - 186	Magenta
	187 - 203	Turquoise
	204 - 220	Orange
221 - 237	Cold White	
238 - 255	Warm White	

3-CHANNEL MODE 1		
CHANNEL	VALUE	FUNCTION
CH1	000 - 255	Master dimmer (0 - 100%)
CH2	000 - 255	Stroboscope (rate 0 - 100%)
CH3	000 - 080	Colour Macros:
	000 - 004	Blackout
	005 - 010	Red
	011 - 015	Green
	016 - 020	Blue
	021 - 025	White
	026 - 030	Amber
	031 - 035	UV
	036 - 040	Yellow
	041 - 045	Cyan
	046 - 050	Lavender
	051 - 055	Light Green
	056 - 060	Magenta
	061 - 065	Turquoise
	066 - 070	Orange
	071 - 075	Cold White
	076 - 080	Warm White
081 - 150	Colour change (rate)	
151 - 220	Colour blending (rate)	
221 - 255	Music control (microphone sensitivity)	

3-CHANNEL MODE 2		
CHANNEL	VALUE	FUNCTION
CH1	000 - 255	Red (0 - 100%)
CH2	000 - 255	Green (0 - 100%)
CH3	000 - 255	Blue (0 - 100%)

6-CHANNEL MODE		
CHANNEL	VALUE	FUNCTION
CH1	000 - 255	Red (0 - 100%)
CH2	000 - 255	Green (0 - 100%)
CH3	000 - 255	Blue (0 - 100%)
CH4	000 - 255	White (0 - 100%)
CH5	000 - 255	Amber (0 - 100%)
CH6	000 - 255	UV (0 - 100%)

9-CHANNEL MODE		
CHANNEL	VALUE	FUNCTION
CH1	000 - 255	Master dimmer (0 - 100%)
CH2	000 - 255	Stroboscope (rate 0 - 100%)
CH3	000 - 255	Red (0 - 100%)
CH4	000 - 255	Green (0 - 100%)
CH5	000 - 255	Blue (0 - 100%)
CH6	000 - 255	White (0 - 100%)
CH7	000 - 255	Amber (0 - 100%)
CH8	000 - 255	UV (0 - 100%)
CH9	000 - 080	Colour Macros:
	000 - 004	Blackout / Colour Mixing CH3 - CH5
	005 - 010	Red
	011 - 015	Green
	016 - 020	Blue
	021 - 025	White
	026 - 030	Amber
	031 - 035	UV
	036 - 040	Yellow
	041 - 045	Cyan
	046 - 050	Lavender
	051 - 055	Light Green
	056 - 060	Magenta
	061 - 065	Turquoise
	066 - 070	Orange
	071 - 075	Cold White
	076 - 080	Warm White
081 - 150	Colour Change (rate)	
151 - 220	Colour Blending (rate)	
221 - 255	Music control (microphone sensitivity)	