

LED UV FLAT PAR

DMX CONTROL TABLE



1-Channel Mode					
Ch.	Function	Values			
1	Dimmer	000	-	255	0% to 100%

2-Channel Mode					
Ch.	Function	Values			
1	Dimmer	000	-	255	0% to 100%
2	Strobe	000	-	005	Strobe open
		006	-	255	Strobe slow -> fast <1Hz - 20Hz

3-Channel Mode					
Ch.	Function	Values			
1	Dimmer	000	-	255	0% to 100%
2	Strobe	000	-	005	Strobe open
		006	-	255	Strobe slow -> fast <1Hz - 20Hz
3	Duration	000	-	255	Flash duration (1ms to 500ms)