

# FREQUENCY LIST

FREQUENZLISTE | LISTE DE FRÉQUENCES | LISTA DE FRECUENCIAS  
WYKAZ CZĘSTOTLIWOŚCI | ELENCO DELLE FREQUENZE



## WIRELESS IN-EAR MONITORING

### LDMEI100G2B5

584 - 607 MHz

	Group 1	Group 2	Group 3	Group 4	Group 5	Group 6	Group 7	Group 8	Group 9	Group 10
Channel 1	584.400	585.250	584.200	585.775	585.100	584.425	584.700	585.550	584.500	586.075
Channel 2	587.500	586.500	585.675	586.500	587.225	586.400	587.800	586.800	585.975	586.800
Channel 3	589.575	588.225	586.800	590.200	588.550	589.425	589.875	588.525	587.100	590.500
Channel 4	591.050	590.725	588.450	591.600	590.575	591.475	591.350	591.025	588.750	591.900
Channel 5	593.425	592.350	589.750	592.700	592.900	593.775	593.725	592.650	590.050	593.000
Channel 6	595.200	593.550	592.200	594.250	596.500	597.675	595.500	593.850	592.500	594.550
Channel 7	598.450	597.800	594.325	595.500	597.750	599.800	598.750	598.100	594.525	595.800
Channel 8	599.650	598.575	598.225	599.100	599.300	602.250	599.950	598.875	598.525	599.400
Channel 9	601.275	600.950	600.525	601.425	600.400	603.550	601.575	601.250	600.825	601.725
Channel 10	603.775	602.425	602.575	603.450	601.800	605.200	604.075	602.725	602.875	603.750
Channel 11	605.500	604.500	605.600	604.775	603.500	606.325	605.800	604.800	605.900	605.075
Channel 12	606.750	607.600	607.575	606.900	606.225	607.800	607.050	607.900	607.875	607.200

### LDMEI100G2B6

655 - 679 MHz

	Group 1	Group 2	Group 3	Group 4	Group 5	Group 6	Group 7	Group 8	Group 9	Group 10
Channel 1	655.400	656.250	655.200	656.775	656.100	655.425	655.700	656.550	655.500	657.075
Channel 2	658.500	657.500	656.675	659.500	657.225	657.400	658.800	657.800	656.975	659.800
Channel 3	660.575	659.225	657.800	661.200	659.550	660.425	660.875	659.825	658.100	661.500
Channel 4	662.050	661.725	659.450	662.600	661.575	662.475	662.350	662.025	659.750	662.900
Channel 5	664.425	663.350	660.750	663.700	663.900	664.775	664.725	663.650	660.050	664.000
Channel 6	666.200	664.550	663.200	665.250	667.500	668.675	666.500	664.850	663.500	665.550
Channel 7	669.450	667.800	665.325	666.500	668.750	670.800	669.750	668.100	665.525	666.800
Channel 8	670.650	669.575	669.225	670.100	670.300	673.250	670.950	669.875	669.525	670.400
Channel 9	672.275	671.950	671.525	672.425	671.400	674.550	672.575	672.250	671.825	672.725
Channel 10	674.775	673.425	673.575	674.450	672.800	676.200	675.075	673.725	673.875	674.750
Channel 11	676.500	675.500	676.600	675.775	674.500	677.325	676.800	675.800	676.900	676.075
Channel 12	677.750	678.600	678.575	677.900	677.225	678.800	678.050	678.900	678.875	678.200

## FREQUENCY LIST

FREQUENZLISTE | LISTE DE FRÉQUENCES | LISTA DE FRECUENCIAS  
WYKAZ CZĘSTOTLIWOŚCI | ELENCO DELLE FREQUENZE



## WIRELESS IN-EAR MONITORING

### LDMEI100G2

823 - 832 / 863 - 865 MHz

	Group 1	Group 2	Group 3	Group 4	Group 5	Group 6	Group 7	Group 8
Channel 1	863.100	863.100	863.200	863.150	863.150	863.100	863.250	863.250
Channel 2	863.500	863.500	863.700	863.550	863.950	863.700	863.650	863.850
Channel 3	864.300	864.000	864.100	864.050	864.450	864.500	864.150	864.350
Channel 4	864.900	864.800	864.800	864.850	864.850	864.900	864.750	864.750
Channel 5	823.100	823.100	823.200	823.150	823.100	823.100	823.150	823.250
Channel 6	823.500	823.700	823.800	823.750	823.700	823.600	823.850	823.950
Channel 7	824.100	824.700	824.600	824.750	824.700	824.600	824.850	824.950
Channel 8	825.500	825.800	825.600	825.850	825.800	825.300	825.650	825.750
Channel 9	826.300	826.500	826.800	826.550	826.500	826.200	826.850	826.950
Channel 10	828.900	827.700	828.100	827.750	827.700	827.300	828.250	828.350
Channel 11	830.100	829.100	829.600	829.150	829.100	829.200	829.550	829.650
Channel 12	831.900	830.600	831.300	831.650	830.600	831.600	831.150	831.250

# FREQUENCY LIST

FREQUENZLISTE | LISTE DE FRÉQUENCES | LISTA DE FRECUENCIAS  
WYKAZ CZĘSTOTLIWOŚCI | ELENCO DELLE FREQUENZE



## WIRELESS IN-EAR MONITORING

### LDMEI1000G2B5

584 - 607 MHz

	Group 1	Group 2	Group 3	Group 4	Group 5	Group 6	Group 7	Group 8	Group 9	Group 10
Channel 1	584.400	585.250	584.200	585.775	585.100	584.425	584.700	585.550	584.500	586.075
Channel 2	587.500	586.500	585.675	586.500	587.225	586.400	587.800	586.800	585.975	586.800
Channel 3	589.575	588.225	586.800	590.200	588.550	589.425	589.875	588.525	587.100	590.500
Channel 4	591.050	590.725	588.450	591.600	590.575	591.475	591.350	591.025	588.750	591.900
Channel 5	593.425	592.350	589.750	592.700	592.900	593.775	593.725	592.650	590.050	593.000
Channel 6	595.200	593.550	592.200	594.250	596.500	597.675	595.500	593.850	592.500	594.550
Channel 7	598.450	597.800	594.325	595.500	597.750	599.800	598.750	598.100	594.525	595.800
Channel 8	599.650	598.575	598.225	599.100	599.300	602.250	599.950	598.875	598.525	599.400
Channel 9	601.275	600.950	600.525	601.425	600.400	603.550	601.575	601.250	600.825	601.725
Channel 10	603.775	602.425	602.575	603.450	601.800	605.200	604.075	602.725	602.875	603.750
Channel 11	605.500	604.500	605.600	604.775	603.500	606.325	605.800	604.800	605.900	605.075
Channel 12	606.750	607.600	607.575	606.900	606.225	607.800	607.050	607.900	607.875	607.200

### LDMEI1000G2B6

655 - 679 MHz

	Group 1	Group 2	Group 3	Group 4	Group 5	Group 6	Group 7	Group 8	Group 9	Group 10
Channel 1	655.400	656.250	655.200	656.775	656.100	655.425	655.700	656.550	655.500	657.075
Channel 2	658.500	657.500	656.675	659.500	657.225	657.400	658.800	657.800	656.975	659.800
Channel 3	660.575	659.225	657.800	661.200	659.550	660.425	660.875	659.825	658.100	661.500
Channel 4	662.050	661.725	659.450	662.600	661.575	662.475	662.350	662.025	659.750	662.900
Channel 5	664.425	663.350	660.750	663.700	663.900	664.775	664.725	663.650	660.050	664.000
Channel 6	666.200	664.550	663.200	665.250	667.500	668.675	666.500	664.850	663.500	665.550
Channel 7	669.450	667.800	665.325	666.500	668.750	670.800	669.750	668.100	665.525	666.800
Channel 8	670.650	669.575	669.225	670.100	670.300	673.250	670.950	669.875	669.525	670.400
Channel 9	672.275	671.950	671.525	672.425	671.400	674.550	672.575	672.250	671.825	672.725
Channel 10	674.775	673.425	673.575	674.450	672.800	676.200	675.075	673.725	673.875	674.750
Channel 11	676.500	675.500	676.600	675.775	674.500	677.325	676.800	675.800	676.900	676.075
Channel 12	677.750	678.600	678.575	677.900	677.225	678.800	678.050	678.900	678.875	678.200

## FREQUENCY LIST

FREQUENZLISTE | LISTE DE FRÉQUENCES | LISTA DE FREQUENCIAS  
WYKAZ CZĘSTOTLIWOŚCI | ELENCO DELLE FREQUENZE



## WIRELESS IN-EAR MONITORING

### LDMEI1000G2

823 - 832 / 863 - 865 MHz

	Group 1	Group 2	Group 3	Group 4	Group 5	Group 6	Group 7	Group 8
Channel 1	863.100	863.100	863.200	863.150	863.150	863.100	863.250	863.250
Channel 2	863.500	863.500	863.700	863.550	863.950	863.700	863.650	863.850
Channel 3	864.300	864.000	864.100	864.050	864.450	864.500	864.150	864.350
Channel 4	864.900	864.800	864.800	864.850	864.850	864.900	864.750	864.750
Channel 5	823.100	823.100	823.200	823.150	823.100	823.100	823.150	823.250
Channel 6	823.500	823.700	823.800	823.750	823.700	823.600	823.850	823.950
Channel 7	824.100	824.700	824.600	824.750	824.700	824.600	824.850	824.950
Channel 8	825.500	825.800	825.600	825.850	825.800	825.300	825.650	825.750
Channel 9	826.300	826.500	826.800	826.550	826.500	826.200	826.850	826.950
Channel 10	828.900	827.700	828.100	827.750	827.700	827.300	828.250	828.350
Channel 11	830.100	829.100	829.600	829.150	829.100	829.200	829.550	829.650
Channel 12	831.900	830.600	831.300	831.650	830.600	831.600	831.150	831.250

## FREQUENCY LIST

FREQUENZLISTE | LISTE DE FRÉQUENCES | LISTA DE FRECUENCIAS  
WYKAZ CZĘSTOTLIWOŚCI | ELENCO DELLE FREQUENZE



# WIRELESS MICROPHONES DISCONTINUED PRODUCTS

## LDMEI100X

838 - 865 MHz

	Group 1	Group 2	Group 3	Group 4	Group 5	Group 6	Group 7	Group 8	Group 9	Group 10
Channel 1	838.850	838.875	838.900	838.925	838.950	839.400	839.425	839.475	841.450	863.100
Channel 2	840.600	839.450	840.525	840.550	840.575	840.650	841.225	841.425	842.300	863.900
Channel 3	842.050	840.625	841.125	841.150	841.200	842.125	842.150	842.250	843.675	864.500
Channel 4	843.100	841.100	842.025	842.075	842.100	843.600	843.625	843.650	845.200	864.900
Channel 5	845.775	842.000	843.050	843.550	843.575	845.100	845.125	845.150	849.175	863.200
Channel 6	846.850	843.025	844.800	844.825	844.850	847.475	849.125	849.150	850.050	863.300
Channel 7	847.400	844.775	845.075	845.250	845.800	848.650	850.025	850.175	850.575	863.400
Channel 8	848.625	845.050	846.900	846.925	846.950	849.475	851.075	851.600	851.625	863.500
Channel 9	850.125	846.875	848.550	847.450	848.600	850.300	853.075	853.100	853.125	863.600
Channel 10	852.800	847.425	849.425	848.575	849.450	851.575	855.425	855.450	856.650	863.700
Channel 11	854.950	848.525	850.200	849.225	850.250	853.050	856.575	856.625	857.200	863.800
Channel 12	856.600	849.100	851.100	850.225	851.550	854.900	857.150	857.175	858.125	864.000
Channel 13	858.000	850.000	852.825	851.050	854.875	855.475	858.100	858.075	859.075	864.100
Channel 14	859.650	851.025	853.750	852.850	856.525	856.550	859.025	859.050	859.600	864.200
Channel 15	860.775	852.775	854.850	853.775	857.100	857.125	860.800	860.825	860.850	864.300
Channel 16	861.300	853.800	855.400	857.450	858.025	858.050	861.800	861.750	861.275	864.400

## LDMEI1000X

838 - 865 MHz

	Group 1	Group 2	Group 3	Group 4	Group 5	Group 6	Group 7	Group 8	Group 9	Group 10
Channel 1	838.850	838.875	838.900	838.925	838.950	839.400	839.425	839.475	841.450	863.100
Channel 2	840.600	839.450	840.525	840.550	840.575	840.650	841.225	841.425	842.300	863.900
Channel 3	842.050	840.625	841.125	841.150	841.200	842.125	842.150	842.250	843.675	864.500
Channel 4	843.100	841.100	842.025	842.075	842.100	843.600	843.625	843.650	845.200	864.900
Channel 5	845.775	842.000	843.050	843.550	843.575	845.100	845.125	845.150	849.175	863.200
Channel 6	846.850	843.025	844.800	844.825	844.850	847.475	849.125	849.150	850.050	863.300
Channel 7	847.400	844.775	845.075	845.250	845.800	848.650	850.025	850.175	850.575	863.400
Channel 8	848.625	845.050	846.900	846.925	846.950	849.475	851.075	851.600	851.625	863.500
Channel 9	850.125	846.875	848.550	847.450	848.600	850.300	853.075	853.100	853.125	863.600
Channel 10	852.800	847.425	849.425	848.575	849.450	851.575	855.425	855.450	856.650	863.700
Channel 11	854.950	848.525	850.200	849.225	850.250	853.050	856.575	856.625	857.200	863.800
Channel 12	856.600	849.100	851.100	850.225	851.550	854.900	857.150	857.175	858.125	864.000
Channel 13	858.000	850.000	852.825	851.050	854.875	855.475	858.100	858.075	859.075	864.100
Channel 14	859.650	851.025	853.750	852.850	856.525	856.550	859.025	859.050	859.600	864.200
Channel 15	860.775	852.775	854.850	853.775	857.100	857.125	860.800	860.825	860.850	864.300
Channel 16	861.300	853.800	855.400	857.450	858.025	858.050	861.800	861.750	861.275	864.400